

Product sheet



LEGRAND

Safety transformer - 230 V / 12 or 24 V - 63 VA

REF. 413098 | EAN. 3245064130981



[> Visit e-catalogue](#)

Product characteristics

- Transformers, buzzers and bells
- Safety transformers - Conform to IEC / EN 61558 - 2 - 6 - Protected against overloads and short circuits. - In the event of an overload, switch "OFF" the power supply and allow the transformer to cool down before switching on again - Wall or rail mounting (for 4 modules) 230 V/12 or 24 V (per coupling 2 x 12 V for Cat.No 4 130 98) - Supplied with strip - P : 63 VA - No - load loss : 4 W - Voltage % drop $\cos \phi = 1$: 15.7 - Efficiency % $\cos \phi = 1$: 75 - Ucc : 13.6 % - I primary loaded : 0,33 A - Number of modules : 5

Documentation

TECHNICAL DOCUMENTATION

-  F01391EN-02.pdf | PDF (0.23Mo)
-  F01391FR-02.pdf | PDF (0.23Mo)



CAD & Design specs / BIM

-  413097.dwg | DWG (0.07Mo)

CATALOGUE PAGE & OTHERS

-  ex223001_0110.pdf | PDF (0.1Mo)

Agreements & Certificates

-  NF-630193A | (0.43Mo)
-  LGRP-2015-168-V1-EN.pdf | PDF (0.63Mo)